



Symbol MC9060: Installing RFlex CE

The following procedures are for a Symbol MC 9060 with Pocket PC 2003 installed. (Note: T=Terminal, PC=Computer). You will need the following:

- Microsoft ActiveSync connection (cradle, serial adapter, etc.)
- RFlex CE Software from Genesta in a folder called RFlex on the PC

Copy RFlexCE Files to Terminal

- [T] Put the terminal into the communication cradle and sync it with the PC using Activesync.
- [PC] On the Activesync screen, after the connection has been made, click the **Explore** icon on the toolbar. Double-click the **My Windows Mobile-Based Device** icon at the top of the file list, then double-click the **Application** folder. Note – the handheld icon may also be called My Pocket PC.
- [PC] Copy the folder **RFlex** from the PC to the Application folder on the terminal. Tap **OK** button on the “File Conversion” message box.
- [T] Tap **Start | Programs | File Explorer**. Tap the directory bar at the top, then tap **My Device** to get to the root directory of the terminal. Tap **Application** to open the folder, then tap **RFlex** to open the folder where the files are.
- [T] Tap and hold the **Gen** file and tap **Copy** from the list. Tap **RFlex** on the directory bar and tap **Application** from the list to go to that folder. Tap and hold in an open area and select **Paste** from the list.

Cold Boot Terminal and Perform “Welcome” Procedures

- [T] Cold Boot terminal. If unit has been without power for a time, inserting the battery will start a cold boot. Otherwise, power on the unit, then press and hold the power button. After 5 seconds, the screen will change to one with the Symbol logo and at the top it will say “Release pwr key to warm boot”. Continue to hold the power key down until the screen goes blank. The entire process takes about 30 seconds.
- [T] After the cold boot completes, at the “Windows Mobile” screen, tap it to begin the setup process.
- [T] Perform the screen alignment by tapping the screen **target** where the 2 lines intersect 5 times (follow the onscreen instructions).
- [T] On the “stylus” screen, tap the **Next** button at the bottom.



- [T] At the “pop-up menus” screen, tap and hold the entry and tap **Cut** in the drop-down menu. Tap and hold the 11th on the calendar and tap **Paste** from the drop-down menu. Tap **Next** button at the bottom.
- [T] At the “location” screen, use the drop-down menu to select the appropriate time zone. Tap **Next** button at the bottom.
- [T] At the “complete” screen, tap the screen to begin to use the terminal.
- [T] The RFlex installation will begin. Tap **OK** at the screen telling you to install the Symbol support CAB file.

Run RFlexCE

- [T] Tap **Start | Programs | RFlex**. The very first time that RFlex runs, it will cause a warm boot. Repeat the process of tapping **Start | Programs | RFlex**. Tap **Option** at the bottom of the display and tap **Configuration**.
- [T] Enter the password “**rfctrl**”.
- [T] Enter the Host IP Address, the Host Port, enter the Unit ID for the terminal (you should get these values from your supervisor) and set the Communication timeout value (15 seconds is standard).
- [T] Tap **OK** to save the settings and return to the Logon screen.
- [T] Tap **Logon** bar. You should be taken to the “RFlex License” screen. Copy down the terminal model number, serial number, and Product ID from the display. Call Genesta to request a key (phone number is on-screen). When you get the key, enter it into the “License Key” field and tap **OK**. Tap **OK** on the “Thank You” box.
- [T] Tap **Logon** bar. If the wireless settings and the RFlex host settings are all correct, you should see the opening “TRICEPS login” screen. Log in and begin work.